

Technical Data Sheet



Desktop Gooseneck Microphone PTT Model DT-GN

Description

The DT-GN Desktop Microphone PTT, provides a means of placing Telex's Gooseneck Microphone, model GNM-18, in a convenient location on your desktop. It is the ideal solution when you want to optimize your workspace environment.

The desktop mount is designed to easily convert the gooseneck microphone (sold separately or included), into a desktop microphone. Connect the microphone to your system with our HB-3Plus Headset Adapter Panel (required interface, not included).

With the PTT feature, you control when the audio is in transmit mode. The red light on the top of the unit indicates when push-to-talk is active.

Optional

Gooseneck Microphone:

The Desktop Gooseneck Microphone PTT unit ships with or without Telex's GNM-18 Gooseneck Microphone

Specifications

Dimensions: 4"W X 5"L X 2.5"H (102mmW X 127mm L X 64mm H)


Weight: 0.24 lbs

Connector: RJ Type, 6 conductor

System Requirements

Hardware: HB-3Plus Headset Adapter Panel

Gooseneck Microphone GNM-18 (if ordering without microphone).



Connector pin out and function

- 1) GND
- 2) Mic
- 3) GND
- 4) PTT Sw
- 5) MON Sw
- 6) +Bias

Installation

No special tools are required for installation. Hand turn the gooseneck microphone into the Desktop Gooseneck Microphone PTT, to the right, and tighten to secure. Attach the cable (included) to the back of the Desktop Gooseneck Microphone PTT and the other end of the cable to the HB-3Plus Headset Adapter Panel *DESK MIC* port, to connect to your system.

Note: The HB-3Plus Headset Adapter Panel is the required interface for connecting to your system.

Included Parts

Gooseneck Microphone Monitor Mount RJ-12 Cable (6 ft long) Vega CD Gooseneck Microphone GNM-18 (optional)

Order information

Part number

Telex Communications
Bosch Communications
8601 East Cornhuskers Hwy
Lincoln NE 68507-9702
Sales Support 1-800-752-7560
http://www.telex.com/RadioDispatch/